Light element, LED, blue, front mount, 12-30VAC/DC, screw connection



Part no. M22-LED-B

218057

EL Number 4355370

(Norway)

General specifications	
Product name	Eaton Moeller® series M22 Accessory LED
Part no.	M22-LED-B
EAN	4015082180577
Product Length/Depth	38 millimetre
Product height	10 millimetre
Product width	37 millimetre
Product weight	0.011 kilogram
Compliances	CE Marked
Certifications	UL 508 EN 60947-5 CSA Std. C22.2 No. 14-05 CSA Std. C22.2 No. 94-91 IEC 60947-5 VDE CSA Class No.: 3211-03 IEC 60947-5-1 CSA UL File No.: E29184 CSA-C22.2 No. 94-91 CSA File No.: 012528 UL IEC/EN 60947-5 CE CSA-C22.2 No. 14-05 UL Category Control No.: NKCR
Product Tradename	M22
Product Type	Accessory
Product Sub Type	LED
Features & Functions	
Fitted with:	Light source Diode
Light color	Blue
General information	
Degree of protection	IP20
Lifespan, electrical	100,000 h (at 25°C, according to EN60064)
Operating torque	0.8 N·m
Overvoltage category	III
Pollution degree	3
Rated impulse withstand voltage (Uimp)	6000 V AC
Туре	LED lamp
Voltage type	AC/DC
Ambient conditions, mechanical	
Mounting position	As required
Shock resistance	Mechanical, According to IEC/EN 60068-2-27 30 g, Mechanical, According to IEC/EN 60068-2-27, Sinusoidal shock 11 ms
Climatic environmental conditions	
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	70 °C
Ambient storage temperature - min	40 °C
Ambient storage temperature - max	80 °C
Climatic proofing	Damp heat, cyclic, to IEC 60068-2-30 Damp heat, constant, to IEC 60068-2-78
Terminal capacities	
Terminal capacity (solid)	0.75 - 2.5 mm ²

Electrical rating Max. 0.25 W Rated organization voltage (Us) Rated organization voltage (Us) Rated organization voltage (Us) Rated organization current (Us) - min Rated organization voltage (Us) at AC - mix Rated organization voltage (Us) at DC - mix Rated dissipation, capacity Policia DV Rated dissipation, capacity Policia Rated dissipation, one current dependent Pvid DV Rated dissipation organization voltage (Us) at DC - mix AC - mix	Terminal capacity (stranded)	0.5 - 2.5 mm ²
Power consumption Rated instalation voltage (UI) SSE V Rated operational current (III - min Fated operational current (III - min Fated operational current (III - min Fated operational current (III - min Rated operational voltage (UII at AC - min Rated operational voltage (UII at AC - min Rated operational voltage (UII at AC - min Rated operational voltage (UII at DC - min Rated operational voltage (UII at CD - min Rated operational current (III at CD - min Rated (III at CD - min R	Electrical rating	
Risted operational current (te) - min Rated operational current (te) - min Rated operational current (te) - max Rated operational voltage (Vel at AC - max Rated operational voltage (Vel at AC - min 12 V Rated operational voltage (Vel at AC - min 12 V Rated operational voltage (Vel at AC - min 12 V Communication Connection to SmartVire-DT Connection type Contacts Force for positive operang - min Design verification Registrated operational voltage (Vel at AC - min Registrated (Vel at AC - max Registrated (Vel a		Max. 0.26 W
Rated operational voltage (Us) at AC - max Rated operational voltage (Us) at AC - max Rated operational voltage (Us) at AC - max Rated operational voltage (Us) at DC - min 12 V Communication Connection is Smart/Wire-DT No Contaction Equipment heat dissipation, current-dependent Pvd 0 W Rated operational current for specified heat dissipation (In) Quality of the smart is smart/Wire-DT Rated operational current for specified heat dissipation (In) Quality of the smart is smart/Wire-DT Rated operational current for specified heat dissipation (In) Quality of the smart is smart/Wire-DT Rated operational current for specified heat dissipation (In) Quality of the small stability of enclosures Meets the product standard's requirements. Quality of the small stability of enclosures Meets the product standard's requirements. Quality of the small stability of enclosures Meets the product standard's requirements. Quality of the small stability of enclosures Quality of the small standard's requirements. Qua	·	500 V
Rated operational voltage (Ue) at AC - max Rated operational voltage (Ue) at AC - min Rated operational voltage (Ue) at DC - max Rated operational voltage (Ue) at DC - min Rated operational voltage	Rated operational current (le) - min	5 mA
Rated operational voltage (Ue) at AC - max Rated operational voltage (Ue) at AC - min Rated operational voltage (Ue) at DC - max Rated operational voltage (Ue) at DC - min Rated operational voltage		14 mA
Rated operational voltage (Ue) at DC - max Rated operational voltage (Ue) at DC - min Communication Connection to SmartWire-DT Connection type Front fixing Pront fixing Contacts Force for positive opening - min Dossign verification Equipment heat dissipation, current-dependent Pvid OW Heat dissipation rapacity Pridiss Heat dissipation par pole, current-dependent Pvid OW Heat dissipation are pole, current-dependent Pvid OW Static heat dissipation, non-current-dependent Pvid OW Static heat dissipation, non-current-dependent Pvid OX Static heat dissipation, non-current-dependent Pvid Do.2.3 Verification 10.2.2.1 Verification of resistance of insulating materials to normal heat 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.2 Sessist of insul. mat. to abnormal heat/fire by intornal elect. effects Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (IV/1 radiation) 10.2.5 Mine, and the product standard's requirements. 10.2.5 Lifting 10.2.6 Mechanical impact Does not apply, since the enrific avvitchpear needs to be evaluated. Does not apply, since the enrific avvitchpear needs to be evaluated. 10.3 Degree of protection of assemblies 10.4 Clearances and crespage distances 10.5 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.6 Roosections for external conductors 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.9 Thermal electric circuits and connections 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.9 Thermal electric circuits and connections 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.9 Thermal electric circuits and connections 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.1 Thermal electric circu	Rated operational voltage (Ue) at AC - max	30 V
Rated operational voltage (Ue) at DC - max Rated operational voltage (Ue) at DC - min Communication Connection to SmartWire-DT Connection type Front fixing Pront fixing Contacts Force for positive opening - min Dossign verification Equipment heat dissipation, current-dependent Pvid OW Heat dissipation rapacity Pridiss Heat dissipation par pole, current-dependent Pvid OW Heat dissipation are pole, current-dependent Pvid OW Static heat dissipation, non-current-dependent Pvid OW Static heat dissipation, non-current-dependent Pvid OX Static heat dissipation, non-current-dependent Pvid Do.2.3 Verification 10.2.2.1 Verification of resistance of insulating materials to normal heat 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.2 Sessist of insul. mat. to abnormal heat/fire by intornal elect. effects Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (IV/1 radiation) 10.2.5 Mine, and the product standard's requirements. 10.2.5 Lifting 10.2.6 Mechanical impact Does not apply, since the enrific avvitchpear needs to be evaluated. Does not apply, since the enrific avvitchpear needs to be evaluated. 10.3 Degree of protection of assemblies 10.4 Clearances and crespage distances 10.5 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.6 Roosections for external conductors 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.9 Thermal electric circuits and connections 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.9 Thermal electric circuits and connections 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.9 Thermal electric circuits and connections 10.8 Frostection against electric shock Does not apply, since the enrific avvitchpear needs to be evaluated. 10.1 Thermal electric circu	· · ·	12 V
Connection to SmartWire-DT Connection type Contacts Froce for positive opening - min Design verification Equipment heat dissipation, current-dependent Pvid Neat dissipation, current-dependent Pvid Neat dissipation per pole, current-dependent Pvid Neat dissipation of resistance or ultra-violet [UII] rediation Neat the product standard's requirements. Nees the product standard's requirements. Nees the product standard's requirements. Neat the product standa		30 V
Connection to SmartWire-DT Connection type Contacts Force for positive opening - min Design verification Equipment heat dissipation, current-dependent Pvid Heat dissipation capacity Pdiss Heat dissipation capacity Pdiss DW Heat dissipation per pole, current-dependent Pvid DW Static heat dissipation per pole, current-dependent Pvid DW Static heat dissipation per pole, current-dependent Pvid DW Static heat dissipation per pole, current-dependent Pvid DA Static heat dissipation per pole, current-dependent Pvis DA Static heat dissipation of mon-current-dependent Pvis DA Static heat dissipation of resistance Meets the product standard's requirements. Da Da Static heat product standard's requirements. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire switchgear needs to be evaluated. Daes not apply, since the entire sw	Rated operational voltage (Ue) at DC - min	12 V
Contacts Force for positive opening - min Design verification Equipment hat dissipation, current-dependent Pvid Heat dissipation capacity Pdiss Net dissipation per pole, current-dependent Pvid Heat dissipation per pole, current-dependent Pvid Net Static heat dissipation, non-current-dependent Pvis 10.22 Corrosion resistance Nests the product standard's requirements. Nests the product stand	Communication	
Contacts Force for positive opening - min DN Design werification DW Equipment heat dissipation, current-dependent Pvid DW Heat dissipation per pole, current-dependent Pvid DW Rated operational current for specified heat dissipation (In) DA Static heat dissipation, nor-current-dependent Pvid DW In 22.2 Corrosion resistance Meets the product standard's requirements. 10.2.3 Everification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of tresistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.3 Resist of insul, mat to a bnormal heat/fire by internal elect, effects Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements. 10.2.5 Lifting Does not apply, since the ordire switchgear needs to be evaluated. 10.2.5 Incorptions Meets the product standard's requirements. 10.2.5 Incorptions Meets the product standard's requirements. 10.2.5 Incorporation of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage staticnes Does not apply, since the entire switchgear nee	Connection to SmartWire-DT	No
Contacts Force for positive opening - min DN Design werification DW Equipment heat dissipation, current-dependent Pvid DW Heat dissipation per pole, current-dependent Pvid DW Rated operational current for specified heat dissipation (In) DA Static heat dissipation, nor-current-dependent Pvid DW In 22.2 Corrosion resistance Meets the product standard's requirements. 10.2.3 Everification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of tresistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.3 Resist of insul, mat to a bnormal heat/fire by internal elect, effects Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements. 10.2.5 Lifting Does not apply, since the ordire switchgear needs to be evaluated. 10.2.5 Incorptions Meets the product standard's requirements. 10.2.5 Incorptions Meets the product standard's requirements. 10.2.5 Incorporation of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage staticnes Does not apply, since the entire switchgear nee	Connection type	Front fixing
Porce for positive opening - min Design verification	Contacts	·
Design verification		0 N
Equipment hest dissipation, current-dependent Pvid Heat dissipation capacity Pdiss 0 W Heat dissipation per pole, current-dependent Pvid Rated operational current for specified heat dissipation (In) 10 A Static heat dissipation, non-current-dependent Pvid 10.2. Static heat dissipation, non-current-dependent Pvis Meets the product standard's requirements. Meets the product standard's requirements. 10.2. Static not insul. mat. to abnormal heat fire by internal elect. effects Meets the product standard's requirements. 10.2. A Resistance to ultra-violet (UV) radiation 10.2. Static not insul. mat. to abnormal heat fire by internal elect. effects Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. 10.2. Despree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. 10.5 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Is the panel builder's responsibility. 10.9 Power-frequency electric strength Is the panel builder's responsibility. Is the panel builder's responsibility. Is the	· · · · · ·	
Heat dissipation capacity Pdiss Heat dissipation prole, current-dependent Pvid 0 W Rated operational current for specified heat dissipation (In) Static heat dissipation, non-current-dependent Pvs 0.45 W 10.22 Corosion resistance Meets the product standard's requirements. 10.23.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.23.2 Verification of resistance of insulating materials to normal heat 10.23.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.24 Resistance to ultra-violat (UV) radiation Meets the product standard's requirements. 10.25 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.27 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creapage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components 10.6 Incorporation of switching devices and components 10.7 Instrail electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9 Power-frequency electric strength 10.9 Power-frequency electric strength 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rading List he panel builder's responsibility. 10.12 Electromagnetic compatibility List he panel builder's responsibility. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction The device meets the requirements, provided the information in the instruction		OW
Heat dissipation per pole, current-dependent Pvid Rated operational current for specified heat dissipation (In) Static heat dissipation, non-current-dependent Pvs 10.22 Corrosion resistance 10.23.1 Verification of frestistance of insulating materials to normal heat 10.23.2 Verification of resistance of insulating materials to normal heat 10.23.3 Resists of insul. mat. to abnormal heat/five by internal elect. effects 10.24 Resistance to ultra-violet (UV) radiation 10.25 Lifting 10.25 Lifting 10.25 Nechanical impact 10.26 Mechanical impact 10.27 Inscriptions 10.30 Dees not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9 Power-frequency electric strength 10.9 Internal electrical circuits and connections 10.9 Internal electrical circuits and connections 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Electromagnetic compatibility 10.15 Protection agents the entire switchgear needs to be evaluated. 10.15 Protection agents the entire switchgear needs to be evaluated. 10.16 Incorporation of switching devices and components 10.17 Internal electrical circuits and connections 10.18 Incorporation of switching devices and components 10.19 Temperature rise entire switchgear needs to be evaluated. 10.19 Temperature rise calculation of the evaluated is the panel builder's responsibility. 10.19 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Mechanical function		
Rated operational current for specified heat dissipation (In) Static heat dissipation, non-current-dependent Pvs 10.22 Corrosion resistance 10.23.1 Verification of thermal stability of enclosures 10.23.2 Verification of thermal stability of enclosures 10.23.3 Resist of insul, mat, to abnormal heat/fire by internal elect, effects 10.23.3 Resist, of insul, mat, to abnormal heat/fire by internal elect, effects 10.24 Resistance to ultra-violet (UV) radiation 10.25 Lifting 10.26 Mechanical impact 10.27 Inscriptions 10.29 Does not apply, since the entire switchgear needs to be evaluated. 10.27 Inscriptions 10.30 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.1 Resting of enclosures made of insulating material 10.10 Temperature rise 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Resisting of enclosures and compatibility 10.15 The device meets the requirements. 10.16 The device meets the requirements.	· · · ·	
Static heat dissipation, non-current-dependent Pvs 10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Resist of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.5 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.5 Incorporation of switching devices and components 10.5 Connections of witching devices and components 10.5 Connections for external conductors 10.5 Connections for external conductors 10.5 Roomections for external conductors 10.5 Power-frequency electric strength 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise The panel builder's responsibility. 10.9.1 The panel builder's responsibility. 10.10 Temperature rise 10.11 Short-circuit rating 10.13 Mechanical function The device meets the requirements, provided the information in the instruction		
10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's requirements. 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects Meets the product standard's requirements. 10.2.4 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements. 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise The panel builder's responsibility. 10.10 Temperature rise The panel builder's responsibility. 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function The device meets the requirements, provided the information in the instruction The device meets the requirements, provided the information in the instruction		
10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.2 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.2.7 Inscriptions 10.2.8 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.8 Incorporation of switching devices and components 10.9 Power-frequency electric strength 10.9 Power-frequency electric strength 10.9.1 Testing of enclosures made of insulating material 10.9.3 Impulse withstand voltage 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.15 Protection of insulation in the instruction 10.14 Ederances and crequirements. 10.15 Protection against electric shock 10.15 Protection against electric shock 10.16 Incorporation of switching devices and components 10.17 Internal electrical circuits and connections 10.18 Incorporation of switching devices and components 10.19 Internal electrical circuits and connections 10.19 Internal electrical circuits and connections 10.10 Temperature rise switchear needs to be evaluated. 10.11 Electromagnetic companishing 10.12 Electromagnetic companishing 10.13 Internal electric switchear must be observed. 10.11 Short-circuit rating 10.12 Electromagnetic companishility 10.13 Mechanical function 10.14 Mechanical function 10.15 Mechanical function 10.16 Mechanical function 10.17 Mechanical function 10.18 Internal electric switchear must be observed. 10.18 Internal electric shoulder's responsibility. The specifications for the switchear mus		
10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3.0 Begree of protection of assemblies 10.3.0 Begree of protection of assemblies 10.4.4 Clearances and creepage distances 10.5.Protection against electric shock 10.5.Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8.1 Sconnections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Electromagnetic compatibility 10.14 Electromagnetic compatibility 10.15 Electromagnetic compatibility 10.16 Internal builder's responsibility. The specifications for the switchgear must be observed. 10.11 Mechanical function 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Mechanical function 10.15 Protection against electric strength 10.16 Internal builder's responsibility. The specifications for the switchgear must be observed. 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Mechanical function 10.15 Protection of switching devices and components 10.16 Protection of switching devices and components 10.17 Internal electric strength 10.18 the panel builder's responsibility. The specifications for the switchgear must be observed. 10.19 Mechanical function 10.19 The device meets the requirements, provided the information in the instruction		
10.2.3 Resist of insul. mat. to abnormal heat/fire by internal elect. effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.12 Electromagnetic compatibility 10.13 Mechanical function Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility. The specifications for the switchgear must be observed. Is the device meets the requirements, provided the information in the instruction		
10.2.4 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements. 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating List the panel builder's responsibility. 10.12 Electromagnetic compatibility 10.13 Mechanical function Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. List the panel builder's responsibility. Is the panel builder's responsibility. The panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility The device meets the requirements, provided the information in the instruction	•	
10.25 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.26 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 10.27 Inscriptions Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Does not apply, since the entire switchgear needs to be evaluated. 10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.10 Temperature rise The panel builder is responsibility. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed.	,	
10.2.6 Mechanical impact 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.12 Electromagnetic compatibility 10.13 Mechanical function Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. In the panel builder's responsibility. It is the panel builder's responsibility. It is the panel builder's responsibility. The specifications for the switchgear must be observed.		
10.27 Inscriptions 10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.12 Electromagnetic compatibility 10.13 Mechanical function Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Incomposition of switching devices and components Is the panel builder's responsibility. The panel builder's responsibility. Is the panel builder's responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed.	·	111
10.3 Degree of protection of assemblies 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.1 Resting of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.12 Electromagnetic compatibility 10.13 Mechanical function Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed. The device meets the requirements, provided the information in the instruction	·	11.7
10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.12 Electromagnetic compatibility 10.13 Mechanical function Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. 10.5 Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	·	· · · · · · · · · · · · · · · · · · ·
10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility. Is the panel builder is responsibility. Is the panel builder is responsibility. Is the panel builder is responsibility. The panel builder's responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed. Is the panel builder's responsibility. The specifications for the switchgear must be observed. The device meets the requirements, provided the information in the instruction		11.17
10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.13 Mechanical function 10.14 Edvice meets the entire switchgear needs to be evaluated. 10.15 Is the panel builder's responsibility. 10.16 Is the panel builder's responsibility. 10.17 Is panel builder's responsibility. 10.18 Is the panel builder's responsibility. 10.19 Is the panel builder's responsibility. 10.10 Temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function 10.14 Electromagnetic provided the information in the instruction		
10.7 Internal electrical circuits and connections 10.8 Connections for external conductors 10.9.2 Power-frequency electric strength 10.9.3 Impulse withstand voltage 10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise 10.11 Short-circuit rating 10.12 Electromagnetic compatibility 10.13 Mechanical function Is the panel builder's responsibility. Is the panel builder is responsibility. Is the panel builder's responsibility. Is the panel builder's responsibility. The specifications for the switchgear must be observed. In the panel builder's responsibility. The specifications for the switchgear must be observed. The device meets the requirements, provided the information in the instruction	· · · · · · · · · · · · · · · · · · ·	THE PERSON NAMED IN THE PE
10.8 Connections for external conductors Is the panel builder's responsibility. 10.9.2 Power-frequency electric strength Is the panel builder's responsibility. 10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility. 10.10 Temperature rise The panel builder is responsibile for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	· · · · · · · · · · · · · · · · · · ·	111
10.9.2 Power-frequency electric strength 1s the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material 1s the panel builder's responsibility. 1o.10 Temperature rise 1o.11 Short-circuit rating 1s the panel builder is responsibility. The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 1s the panel builder's responsibility. The specifications for the switchgear must be observed. 1o.12 Electromagnetic compatibility 1s the panel builder's responsibility. The specifications for the switchgear must be observed. 1o.13 Mechanical function The device meets the requirements, provided the information in the instruction		
10.9.3 Impulse withstand voltage Is the panel builder's responsibility. 10.9.4 Testing of enclosures made of insulating material Is the panel builder is responsibility. The panel builder is responsibile for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction		
10.9.4 Testing of enclosures made of insulating material 10.10 Temperature rise The panel builder is responsibility. The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	. , .	
10.10 Temperature rise The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction		
observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction		The panel builder is responsible for the temperature rise calculation. Eaton will
10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be
	10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be
	10.13 Mechanical function	

Technical data ETIM 8.0

Low-voltage industrial components (EG000017) / Lamp holder block for control circuit devices (EC000204)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Command and alarm device / Bulb socket block for command and alarm devices (eci@ss10.0.1-27-37-12-09 [AKF027014])

(ecl@ss10.0.1-2/-3/-12-09 [AKF02/014])		
Transformer integrated		No
With integrated voltage decreasing resistor		No
With light source		Yes
With integrated diode		Yes
Lamp holder		None
Rated voltage Ue at AC 50 Hz	V	12 - 30

Rated voltage Ue at AC 60 Hz	V	12 - 30
Rated voltage Ue at DC	V	12 - 30
Voltage type for actuating		AC/DC
Lamp type		LED
Connection type auxiliary circuit		Screw connection
Colour lamp		Blue
Type of fastening		Front fastening