## DATASHEET - ZB65-24

## Overload relay, ZB65, Ir= 16 - 24 A, 1 N/O, 1 N/C, Direct mounting, IP00



Part no. EL Number	ZB65-24 278457 4131852	Powering Business Worldwide
(Norway)		
General specifications		
Product name		Eaton Moeller® series ZB Thermal overload relay
Part no.		ZB65-24
EAN Product Length/Depth		4015082784577 88 millimetre
Product Lenguy Depth		75 millimetre
Product width		60 millimetre
Product weight		0.22 kilogram
Certifications		UL CSA-C22.2 No. 60947-4-1-14 VDE 0660 CSA Class No.: 3211-03 CSA File No.: 012528 UL Category Control No.: NKCR CE IEC/EN 60947 IEC/EN 60947-4-1 CSA UL File No.: E29184 UL 60947-4-1
Product Tradename		ZB
Product Type		Thermal overload relay
Product Sub Type		None
Catalog Notes		Ambient air temperature: Operating range to IEC/EN 60947, PTB: -5°C to +55°C Ambient operating temperature (according to IEC/EN 60947) PTB: -5 °C - +55 °C Rated operational current: Switch-on and switch-off conditions based on DC-13, time constant as specified.
Features & Functions		
Features		Test/off button Trip-free release Reset pushbutton manual/auto Phase-failure sensitivity (according to IEC/EN 60947, VDE 0660 Part 102)
General information		
Ambient operating temperature - min		-25 °C
Ambient operating temperature - max		55 °C
Ambient operating temperature (enclosed) - min		25 °C
Ambient operating temperature (enclosed) - max		40 °C
Class		CLASS 10 A
Climatic proofing		Damp heat, cyclic, to IEC 60068-2-30 Damp heat, constant, to IEC 60068-2-78
Degree of protection		IP00
Frame size		ZB65
Mounting method		Direct attachment Direct mounting
Overload release current setting - min		16 A
Overload release current setting - max		24 A
Overvoltage category		III
Pollution degree		3
Product category		Accessories Overload relay ZB up to 150 A
Protection		Finger and back-of-hand proof, Protection against direct contact when actuated from front (EN 50274)
Rated impulse withstand voltage (Uimp)		6000 V AC 4000 V (auxiliary and control circuits)
Shock resistance		10 g, Mechanical, Sinusoidal, Shock duration 10 ms
Suitable for		Branch circuits, (UL/CSA)

Temperature compensation	< 0.25 %/K, residual error for T > 40°
Forminal equation	Continuous
Ferminal capacities	
Terminal capacity (flexible with ferrule)	1 x (0.75 - 2.5) mm², Control circuit cables 2 x (0.75 - 2.5) mm², Control circuit cables 2 x (1 - 25) mm², Main cables 1 × (1 - 25) mm², Main cables
Terminal capacity (solid)	2 x (1 - 16) mm <sup>2</sup> , Main cables 1 x (0.75 - 4) mm <sup>2</sup> , Control circuit cables 1 x (1 - 16) mm <sup>2</sup> , Main cables 2 x (0.75 - 4) mm <sup>2</sup> , Control circuit cables
Terminal capacity (solid/stranded AWG)	14 - 2, Main cables 2 x (18 - 14), Control circuit cables
Terminal capacity (stranded)	1 x (16 - 25) mm², Main cables
Stripping length (main cable)	11 mm
Stripping length (control circuit cable)	8 mm
Screw size	M6, Terminal screw, Main cables M3.5, Terminal screw, Control circuit cables
Screwdriver size	2, Terminal screw, Pozidriv screwdriver 1 x 6 mm, Terminal screw, Standard screwdriver
Tightening torque	3.5 Nm, Screw terminals, Main cables 1.2 Nm, Screw terminals, Control circuit cables
Electrical rating	
Conventional thermal current ith of auxiliary contacts (1-pole, open)	6 A
Rated operational current (Ie) at AC-15, 120 V	1.5 A
Rated operational current (Ie) at AC-15, 220 V, 230 V, 240 V	1.5 A
Rated operational current (Ie) at AC-15, 380 V, 400 V, 415 V	0.9 A
Rated operational current (Ie) at DC-13, 110 V	0.4 A
Rated operational current (Ie) at DC-13, 220 V, 230 V	0.2 A
Rated operational current (Ie) at DC-13, 24 V	0.9 A
Rated operational current (Ie) at DC-13, 60 V	0.75 A
Rated operational voltage (Ue) - max	690 V
Safe isolation	240 V AC, Between auxiliary contacts, According to EN 61140 440 V, Between auxiliary contacts and main contacts, According to EN 61140 440 V AC, Between main circuits, According to EN 61140
Switching capacity (auxiliary contacts, pilot duty)	B600 at opposite polarity, AC operated (UL/CSA) R300, DC operated (UL/CSA) B300 at opposite polarity, AC operated (UL/CSA)
Voltage rating - max	600 V AC
Short-circuit rating	
Short-circuit current rating (basic rating)	90 A, max. CB, SCCR (UL/CSA) 5 kA, SCCR (UL/CSA) 90 A, max. Fuse, SCCR (UL/CSA)
Short-circuit current rating (high fault at 480 V)	100 kA, Fuse, SCCR (UL/CSA) 50 A, max. CB, SCCR (UL/CSA) 65 kA, CB, SCCR (UL/CSA) 45 A, Class J/CC, max. Fuse, SCCR (UL/CSA)
Short-circuit current rating (high fault at 600 V)	100 kA, Fuse, SCCR (UL/CSA) 45 A, Class J/CC, max. Fuse, SCCR (UL/CSA)
Short-circuit protection rating	63 A gG/gL, Fuse, Type "1" coordination Max. 6 A gG/gL, fuse, Without welding, Auxiliary and control circuits 50 A gG/gL, Fuse, Type "2" coordination
Contacts	
Number of auxiliary contacts (change-over contacts)	0
Number of auxiliary contacts (normally closed contacts)	1
Number of auxiliary contacts (normally open contacts)	1
Number of contacts (normally closed contacts)	1
Number of contacts (normally open contacts)	1
Design verification	
Equipment heat dissipation, current-dependent Pvid	5.7 W
Heat dissipation capacity Pdiss	0 W
Heat dissipation per pole, current-dependent Pvid	1.9 W
Rated operational current for specified heat dissipation (In)	24 A
Static heat dissipation, non-current-dependent Pvs	0 W

10.2.2 Corrosion resistanceMeets the product standard's requirements.10.2.3.1 Verification of thermal stability of enclosuresMeets the product standard's requirements.10.2.3.2 Verification of resistance of insulating materials to normal heatMeets the product standard's requirements.10.2.3.2 Verification of resistance of insulating materials to normal heatMeets the product standard's requirements.10.2.3.2 Verification of resistance of insulating materials to normal heatMeets the product standard's requirements.10.2.4 Resistance to ultra-violet (UV) radiationDoes not apply, since the entire switchgear needs to be evaluated.10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Meets the product standard's requirements.Meets the product standard's requirements.10.3.0 Egree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Concretions for switching devices and componentsIs the panel builder's responsibility.10.8.1 Meets the groduct standard's requirements.Is the panel builder's responsibility.10.8.2 Meets the groduct standard's requirements.Is the panel builder's responsibility.10.8.1 Meets the groduct standard's requirements.Is the panel builder's responsibility.10.8.2 Meets the groduct standard's requirements.Is the panel builder's responsibility.10.8.1 Meets the groduct standard's requirements.Is the pane		
10.2.3.2 Verification of resistance of insulating materials to normal heatMeets the product standard's requirements.10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect effectsMeets the product standard's requirements.10.2.4 Resistance to ultra-violet (UV) radiationDoes not apply, since the entire switchgear needs to be evaluated.10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.10.3.0 Begree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.3 Nampulse withstand voltageIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.3 Resist of insul. mat. to abnormal heat/fire by internal elect. effectsMeets the product standard's requirements.10.2.4 Resistance to ultra-violet (UV) radiationMeets the product standard's requirements.10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.8 Connections for external conductorsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.3 Inpulse withstand voltageIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibility.Is the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiationMeets the product standard's requirements.10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.	10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.10.2.7 InscriptionsMeets the product standard's requirements.10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder is responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.6 Mechanical impact   Does not apply, since the entire switchgear needs to be evaluated.     10.2.7 Inscriptions   Does not apply, since the entire switchgear needs to be evaluated.     10.3 Degree of protection of assemblies   Does not apply, since the entire switchgear needs to be evaluated.     10.4 Clearances and creepage distances   Meets the product standard's requirements.     10.5 Protection against electric shock   Does not apply, since the entire switchgear needs to be evaluated.     10.6 Incorporation of switching devices and components   Does not apply, since the entire switchgear needs to be evaluated.     10.7 Internal electrical circuits and connections   Is the panel builder's responsibility.     10.8 Connections for external conductors   Is the panel builder's responsibility.     10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   Is the panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provide the information in the instruction	10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.7 Inscriptions   Meets the product standard's requirements.     10.3 Degree of protection of assemblies   Does not apply, since the entire switchgear needs to be evaluated.     10.4 Clearances and creepage distances   Meets the product standard's requirements.     10.5 Protection against electric shock   Does not apply, since the entire switchgear needs to be evaluated.     10.6 Incorporation of switching devices and components   Does not apply, since the entire switchgear needs to be evaluated.     10.7 Internal electrical circuits and connections   Is the panel builder's responsibility.     10.8 Connections for external conductors   Is the panel builder's responsibility.     10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.10 Temperature rise   The panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.3 Degree of protection of assembliesDoes not apply, since the entire switchgear needs to be evaluated.10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provide the information in the instruction	10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distancesMeets the product standard's requirements.10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.2.7 Inscriptions	Meets the product standard's requirements.
10.5 Protection against electric shockDoes not apply, since the entire switchgear needs to be evaluated.10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility.10.12 Electromagnetic compatibilityIs the panel builder's responsibility.10.13 Mechanical functionIs the panel builder's responsibility.10.13 Mechanical functionIs the panel builder's responsibility.	10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and componentsDoes not apply, since the entire switchgear needs to be evaluated.10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionIs the panel builder's responsibility. The specifications for the switchgear must be observed.	10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.7 Internal electrical circuits and connectionsIs the panel builder's responsibility.10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseThe panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.8 Connections for external conductorsIs the panel builder's responsibility.10.9.2 Power-frequency electric strengthIs the panel builder's responsibility.10.9.3 Impulse withstand voltageIs the panel builder's responsibility.10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.10.10 Temperature riseIs the panel builder's responsibility.10.11 Short-circuit ratingIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.12 Electromagnetic compatibilityIs the panel builder's responsibility. The specifications for the switchgear must be observed.10.13 Mechanical functionThe device meets the requirements, provided the information in the instruction	10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.9.2 Power-frequency electric strength   Is the panel builder's responsibility.     10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   Is the panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage   Is the panel builder's responsibility.     10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   The panel builder is responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material   Is the panel builder's responsibility.     10.10 Temperature rise   Is the panel builder's responsibility.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.10 Temperature rise   The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.     10.11 Short-circuit rating   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.12 Electromagnetic compatibility   Is the panel builder's responsibility. The specifications for the switchgear must be observed.     10.13 Mechanical function   The device meets the requirements, provided the information in the instruction	10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed.   10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed.   10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.12 Electromagnetic compatibility observed.   10.13 Mechanical function Image: Compatibility of the section of the switch and the section of the	10.10 Temperature rise	
10.13 Mechanical function The device meets the requirements, provided the information in the instruction	10.11 Short-circuit rating	
	10.12 Electromagnetic compatibility	
	10.13 Mechanical function	

## **Technical data ETIM 8.0**

Low-voltage industrial components (EG000017) / Thermal overload relay (EC000106)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Overload protection device / Thermal overload relay (ecl@ss10.0.1-27-37-15-01 [AKF075014])					
Adjustable current range	A	١	16 - 24		
Max. rated operation voltage Ue	V	1	690		
Mounting method			Direct attachment		
Type of electrical connection of main circuit			Screw connection		
Number of auxiliary contacts as normally closed contact			1		
Number of auxiliary contacts as normally open contact			1		
Number of auxiliary contacts as change-over contact			0		
Release class			CLASS 10 A		
Reset function input			No		
Reset function automatic			Yes		
Reset function push-button			Yes		